

ZCU106 の GTY バンク

- Quad X0Y4
 - GTHE4_CHANNEL_X0Y19 Bank227 G1,G2,H3,H4; FMC:A15,A14,A35,A34; DIN[5],DOUT[6]; core#2-1
 - GTHE4_CHANNEL_X0Y18 Bank227 J1,J2,K3,K4; FMC:B13,B12,B33,B32; DIN[2],DOUT[2]; core#2-0
 - GTHE4_CHANNEL_X0Y17 Bank227 L1,L2,L5,L6; FMC:A19,A18,A39,A38; DIN[4],DOUT[5]; core#1-1
 - GTHE4_CHANNEL_X0Y16 Bank227 N1,N2,M3,M4; FMC:B17,B16,B37,B36; DIN[3],DOUT[3]; core#1-0
- Quad X0Y3
 - GTHE4_CHANNEL_X0Y15 Bank226 P3,P4,N5,N6; FMC:A7,A6,A27,A26; DIN[0],DOUT[1]; core #0-1
 - GTHE4_CHANNEL_X0Y14 Bank226 R1,R2,R5,R6; FMC:C7,C6,C3,C2; DIN[1],DOUT[0]; core #0-0
 - GTHE4_CHANNEL_X0Y13 Bank226 U1,U2,T3,T4; FMC:A3,A2,A23,A22; DIN[7],DOUT[4]; core #3-1
 - GTHE4_CHANNEL_X0Y12 Bank226 V3,V4,U5,U6; FMC:A11,A10,A31,A30; DIN[6],DOUT[7]; core #3-0
- Quad X0Y2
 - GTHE4_CHANNEL_X0Y11 Bank225 W1,W2,W5,W6
 - GTHE4_CHANNEL_X0Y10 Bank225 AA1,AA2,Y3,Y4
 - GTHE4_CHANNEL_X0Y9 Bank225 AB3,AB4,AA5,AA6
 - GTHE4_CHANNEL_X0Y8 Bank225 AC1,AC2,AC5,AC6
- Quad X0Y1
 - GTHE4_CHANNEL_X0Y6 Bank224 AE1,AE2,AD3,AD4
 - GTHE4_CHANNEL_X0Y5 Bank224 AF3,AF4,AE5,AE6
 - GTHE4_CHANNEL_X0Y5 Bank224 AG1,AG2,AG5,AG6
 - GTHE4_CHANNEL_X0Y4 Bank224 AJ1,AJ2,AH3,AH4
- Quad X0Y0
 - GTHE4_CHANNEL_X0Y3 Bank223 AK3,AK4,AJ5,AJ6
 - GTHE4_CHANNEL_X0Y2 Bank223 AL1,AL2,AL5,AL6
 - GTHE4_CHANNEL_X0Y1 Bank223 AN1,AN2,AM3,AM4
 - GTHE4_CHANNEL_X0Y0 Bank223 AP3,AP4,AN5,AN6